

# WGP-I35/S

## ISUZU SERIES

### Features:

- Rotate speed governor: GAC Electrical governor
- Excitation system: Self excited
- A.V.R model: SX460
- Emergency stop switch
- ATS (automatic transfer switch) receptacle
- 12V sealed for life maintenance free battery
- Lockable battery isolator switch
- Powder coated canopy (Only for Soundproofed sets)
- 50°C radiator
- Oil pump on the engine
- Steel base frame with fork holes
- Vibration isolators between the engine/alternator and base frame
- Dry type air filter
- Base fuel tank for daily running
- Drain points for fuel tank
- Operation Manual / Specifications



### Dimensions and Weights

Model	L	W	H
WGP-I35	/	/	/
WGP-I35S	1850	750	1200

Dimensions for reference. Change or amendment without notice.

### Notes:

#### \*Prime Power

Continuous duty operation, under variable load 24/24h-10% over load

#### \*\*Standby Power

Standby duty, operation under variable load, without over load;

### Standard Reference Conditions

Note: Standard reference conditions 25°C (77°F) Air Inlet Temp, 100m(328 ft) A.S.L. 30% relative humidity. Fuel consumption data at full load with diesel fuel with specific gravity of 0.85 and conforming to BS2869: 1998,

### Output Ratings

Genset Model	Prime Power	Standby Power
WGP-I35	28kW/35kVA	30kW/37kVA
WGP-I35S	28kW/35kVA	30kW/37kVA

Power factor 0.8

### Ratings and Performance Data

Engine Model:	ISUZU 4JB1TA
Alternator Brand:	WALT
Alternator Model:	WGP184H
Control System:	Smartgen HGM420
Circuit Breaker:	Delixi
Frequency & Phase:	50Hz & 3Phase
Engine Speed: RPM	1500
Fuel Tank Capacity: L	
WGP-I35	10 hours
WGP-I35S	10 hours
Noise level	68dB at 7m
Fuel Consumption: l/hr (75% Load)	
- Prime Power	6.73
- Standby Power	7.41
Gross Weight (Kg)	920 KGS
Warranty	12 months or 1500 hrs

**Engine Model: 4JB1TA**

Engine Brand	ISUZU
Model	4JB1TA
No.of Cylinders and Build	4 Cylinder,water cooled, 4 stroke directed injection, Turbocharged
Governor mode	GAC Electrical
Bore×Stroke(mm )	93×102
Compression ratio	18.2:1
Rated speed(rpm)	1500
Displacement(L)	2.779
Rated power(kW)	36
Standby power(kW)	40
Fuel consumption(g/kWh)	218
Max. ambient temperature	50℃
Flywheel housing	SAE 3
The lowest stable speed at zero load (r/min)	≤850
Lubricating system	Pressure splashed
Starting type	Electric starter
Fuel type	0#,-10#,-20#
Lube oil type	CD Grade or SAE 10W-30, 15W-40
Lube oil capacity	8.5 Liters
Cooling water capacity	10 Liters
Starting motor capacity (V.A)	12V,2.8KW
Charging generator capacity (V.A)	12V 50A
Dry weight	275KGS

**Alternator Model: WGP184H**

**Alternator Physical Data**

Manufactured by:	WALT
Model:	184H
No. of Bearings:	/
Insulation Class:	H
Winding Pitch Code:	2/3
Wires:	12
Ingress Protection Rating:	IP23
Excitation System:	Self excited,shunt
AVR Model:	SX460

**Alternator Operating Data**

Overspeed: rpm	2250rpm
Voltage Regulation: (Steady state)	±1.0%
Wave Form NEMA = TIF:	< 50
Wave Form IEC = THF:	< 2%
Air Flow: m3/s	0.1
Altitude: m	≤1000

**Voltage Technical Data WGP-I35**

Voltage	Primary	Standby
V	kVA	kVA
400	35	37
/	/	/
/	/	/
/	/	/

**Voltage Technical Data WGP-I35S**

Voltage	Primary	Standby
V	kVA	kVA
400	35	37
/	/	/
/	/	/
/	/	/

HGM420 ( AMF ) Genset Controller



Features:

- \* HGM420, AMF (Auto Mains Failure), mains electric quantity monitoring and mains/generator automatic transfer control function, especially for automatic system composed by generator and mains
- \* Suitable for 3-phase 4-wire systems with voltage 400V and frequency 50Hz.
- \* Collects and shows 3-phase voltage, current, power parameter and frequency of generator or mains.
- \* For Mains, controller has over voltage, under voltage and loss of phase detection functions; For generator, controller has over voltage, under voltage, over frequency, under frequency and over current detection functions
- \* Precision collect and display parameters about Engine.
- \* Control & Protection: automatic start/stop of the genset, ATS(Auto Transfer Switch) control with perfect fault indication and protection function.

- \* With ETS(Energize To Stop), idle control, pre-heat control, speed raise control and speed drop control function, All output ports are relay-out
- \* Multiplex input port 3 and 4 can be used in various fields: input 3 can be used as auxiliary input port or fuel level sensor while input 4 can be used as auxiliary input port or configurable sensor.
- \* More kinds of curves of temperature, oil pressure, fuel level can be used directly and users can define the sensor curves by themselves,
- \* Multiple crank disconnect conditions (magnetic pickup, oil pressure, generator frequency) are optional
- \* Widely Power supply range: DC(8~35)V, suitable to different start battery voltage environment

Optional

<p>Engine</p> <ul style="list-style-type: none"> <li>• Water Jacket Preheater</li> <li>• Fuel-water separator</li> <li>• Oil pump</li> <li>• Oil preheater</li> <li>• Battery preheater</li> </ul>	<p>Alternator</p> <ul style="list-style-type: none"> <li>• PMG excitation</li> <li>• Alternator heater</li> <li>• Winding Temperature Measuring</li> <li>• Anti-damp and anti-corrosion treatment</li> <li>• Anti-condensation heater</li> </ul>	<p>Generator Set</p> <ul style="list-style-type: none"> <li>• Tools with the machine</li> <li>• Coolant (-30°C)</li> </ul>
<p>Canopy</p> <ul style="list-style-type: none"> <li>• Hired type</li> <li>• Trailer</li> </ul>	<p>Fuel System</p> <ul style="list-style-type: none"> <li>• Low fuel level alarm</li> <li>• Automatic fuel feeding system</li> <li>• Fuel T-valves</li> <li>• Dual Wall Integral Fuel Tanks</li> <li>• Dual Wall Sub-base Fuel Tanks</li> <li>• Automatic Fuel Fill Options</li> <li>• Fuel level shut down sensor</li> </ul>	<p>Control System</p> <ul style="list-style-type: none"> <li>• AMF function</li> <li>• ATS control cabinet</li> <li>• Double HZ &amp; Volt</li> <li>• ABB &amp; MCCB</li> </ul>
<p>Air Inlet system</p> <ul style="list-style-type: none"> <li>• Air pre-heater</li> </ul>	<p>Lube system</p> <ul style="list-style-type: none"> <li>• Manual sump pump</li> <li>• Lubricant oil pre-heater</li> </ul>	<p>Starting /Charging system</p> <ul style="list-style-type: none"> <li>• Jacket water heater</li> </ul>

WALT GLOBAL POWER EQUIPMENT CO.,LTD

E-mail: sales@waltpower.com  
 Walt reserves the right to make changes in model, technical specification, color, configuration and accessories without prior notice.  
 Please contact the salesman before ordering.  
 2018 by WALT, All right reserved